

Eaton MMX34AA014F0-0

Catalog Number: MMX34AA014F0-0

Eaton M-Max Series Adjustable Frequency AC Drives Basic Controller, Full version, AA software design series, EMC filter, FS3 frame, 380-480V, 460V, IP20 enclosure rating, 10 hp, 14A output, 18.7A input, Three-phase in, three-phase out

General specifications

Product Name	Catalog Number
Eaton M-Max Series sensorless vector adjustable frequency drive	MMX34AA014F0-0
	UPC
	786685268866
Product Length/Depth	Product Height
3.94 in	4.27 in
Product Width	Product Weight
10.33 in	2.18 lb
Warranty	Compliances
2 year	RoHS Compliant
	CE Marked
	EMC Category C2, C3, and C4 (Level H): With an internal RFI filter option
	C-Tick Compliant
Certifications	Catalog Notes
cUL Certified	Horsepower ratings are based on the use of a 240V, 460V, and 575V NEMA B, four- or six-pole squirrel cage induction motor and are for reference only.
EN 61800-3	
EN 61800-5-1	
UL Listed	
EN 60204-1	



Product specifications

Frame size

3

Special features

AA software design series, EMC filter

Type

Full version

Phase

Three-phase in, three-phase out

Input current

18.7 A

Horsepower

10 hp

Rating

IP20

Output current - max

14 A

Voltage rating

380-480 V, 460 V

Resources

Brochures

[Variable frequency drive - Product overview](#)

[M-Max Series adjustable frequency drives](#)

Catalogs

[Eaton's Volume 6—Solid-State Motor Control](#)

Drawings

[MMX_\(FR3\) 2D Drawing Xchange](#)

[MMX_\(FR3\) 3D Inventor](#)

[MMX_\(FR3\) AutoCAD 2D Footprint](#)

[MMX_\(FR3\) 2D PDF](#)

[MMX_\(FR3\) AutoCAD 2D Footprint \(mm\)](#)

[MMX_\(FR3\) 3D Model Xchange](#)

Installation instructions

[User Manual, M-Max Series Adjustable Frequency Drive](#)

Specifications and datasheets

[Eaton Specification Sheet - MMX34AA014F0-0](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2023 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)